

# ECLPANELTWC

## CHANNELS DMX

### 1 CHANNEL THEATRE

MODE 1 Ch	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255

### 2 CHANNELS THEATRE

MODE 2 Ch	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>DIMMER FADE</b> Read from menu 0~100%	000 - 000 001 - 255

### 4 CHANNELS THEATRE

MODE 4 Ch	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>CCT</b> 2800K - 3200K 3200K - 3500K 3500K - 4000K 4000K - 4500K 4500K - 5000K 5000K - 5600K 5600K - 6000K 6000K - 6500K	000 - 031 032 - 063 064 - 095 096 - 127 128 - 159 160 - 191 192 - 223 224 - 255
3	<b>HUE</b> 0 -25°~25°	000 - 000 001 - 255
4	<b>DIMMER FADE</b> Read from menu 0~100%	000 - 000 001 - 255

### 5 CHANNELS 1 THEATRE

MODE 5 Ch1	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>DIMMER FINE</b> 0~100%	000 - 255
3	<b>CCT</b> 2800K - 3200K 3200K - 3500K 3500K - 4000K 4000K - 4500K 4500K - 5000K 5000K - 5600K 5600K - 6000K 6000K - 6500K	000 - 031 032 - 063 064 - 095 096 - 127 128 - 159 160 - 191 192 - 223 224 - 255
4	<b>HUE</b> 0 -25°~25°	000 - 000 001 - 255
5	<b>DIMMER FADE</b> Read from menu 0~100%	000 - 000 001 - 255

### 5 CHANNELS 2 THEATRE

MODE 5 Ch2	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>CCT</b> 2800K - 3200K 3200K - 3500K 3500K - 4000K 4000K - 4500K 4500K - 5000K 5000K - 5600K 5600K - 6000K 6000K - 6500K	000 - 031 032 - 063 064 - 095 096 - 127 128 - 159 160 - 191 192 - 223 224 - 255
3	<b>HUE</b> 0 -25°~25°	000 - 000 001 - 255
4	<b>STROBE</b> Closed Strobe slow to fast Open Random slow to fast Open	000 - 030 031 - 100 101 - 130 131 - 200 201 - 255
5	<b>DIMMER FADE</b> Read from menu 0~100%	000 - 000 001 - 255

# ECLPANELTWC

## 6 CHANNELS THEATRE

MODE 6 Ch	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>CCT</b> 2800K - 3200K 3200K - 3500K 3500K - 4000K 4000K - 4500K 4500K - 5000K 5000K - 5600K 5600K - 6000K 6000K - 6500K	000 - 031 032 - 063 064 - 095 096 - 127 128 - 159 160 - 191 192 - 223 224 - 255
3	<b>HUE</b> 0 -25°~25°	000 - 000 001 - 255
4	<b>STROBE</b> Closed Strobe slow to fast Open Random slow to fast Open	000 - 030 031 - 100 101 - 130 131 - 200 201 - 255
5	<b>COLOR MACRO</b> No Function Amber Shift on Color Macro	000 - 002 003 - 005 006 - 255
6	<b>DIMMER FADE</b> Read from menu 0~100%	000 - 000 001 - 255

## 10 CHANNELS THEATRE

MODE 10 Ch	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>RED</b> 0~100%	000 - 255
3	<b>GREEN</b> 0~100%	000 - 255
4	<b>BLUE</b> 0~100%	000 - 255
5	<b>WHITE</b> 0~100%	000 - 255
6	<b>CCT</b> 2800K - 3200K 3200K - 3500K 3500K - 4000K 4000K - 4500K 4500K - 5000K 5000K - 5600K 5600K - 6000K 6000K - 6500K No Function	000 - 030 031 - 060 061 - 090 091 - 120 121 - 150 151 - 180 181 - 210 211 - 240 241 - 255
7	<b>HUE</b> 0 -25°~25°	000 - 000 001 - 255
8	<b>STROBE</b> Closed Strobe slow to fast Open Random slow to fast Open	000 - 030 031 - 100 101 - 130 131 - 200 201 - 255
9	<b>COLOR MACRO</b> No Function Amber Shift on Color Macro	000 - 002 003 - 005 006 - 255
10	<b>DIMMER FADE</b> Read from menu 0~100%	000 - 000 001 - 255

# ECLPANELTWC

## 15 CHANNELS THEATRE

MODE 15 Ch	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>DIMMER FINE</b> 0~100%	000 - 255
3	<b>RED</b> 0~100%	000 - 255
4	<b>RED FINE</b> 0~100%	000 - 255
5	<b>GREEN</b> 0~100%	000 - 255
6	<b>GREEN FINE</b> 0~100%	000 - 255
7	<b>BLUE</b> 0~100%	000 - 255
8	<b>BLUE FINE</b> 0~100%	000 - 255
9	<b>WHITE</b> 0~100%	000 - 255
10	<b>WHITE FINE</b> 0~100%	000 - 255
11	<b>CCT</b> 2800K - 3200K 3200K - 3500K 3500K - 4000K 4000K - 4500K 4500K - 5000K 5000K - 5600K 5600K - 6000K 6000K - 6500K No Function	000 - 030 031 - 060 061 - 090 091 - 120 121 - 150 151 - 180 181 - 210 211 - 240 241 - 255
12	<b>HUE</b> 0 -25°~25°	000 - 000 001 - 255
13	<b>STROBE</b> Closed Strobe slow to fast Open Random slow to fast Open	000 - 030 031 - 100 101 - 130 131 - 200 201 - 255
14	<b>COLOR MACRO</b> No Function Amber Shift on Color Macro	000 - 002 003 - 005 006 - 255
15	<b>DIMMER FADE</b> Read from menu 0~100%	000 - 000 001 - 255

## 17 CHANNELS THEATRE

MODE 17 Ch	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>DIMMER FINE</b> 0~100%	000 - 255
3	<b>STROBE</b> Closed Strobe slow to fast Open Random slow to fast Open	000 - 030 031 - 100 101 - 130 131 - 200 201 - 255
4	<b>CCT</b> 2800K - 3200K 3200K - 3500K 3500K - 4000K 4000K - 4500K 4500K - 5000K 5000K - 5600K 5600K - 6000K 6000K - 6500K	000 - 031 032 - 063 064 - 095 096 - 127 128 - 159 160 - 191 192 - 223 224 - 255
5	<b>HUE</b> -25° to 0 No function 0 to +25°	000 - 126 127 128 - 255
6	<b>CROSSFADE</b> 0~100%	000 - 255
7	<b>RED</b> 0~100%	000 - 255
8	<b>RED FINE</b> 0~100%	000 - 255
9	<b>GREEN</b> 0~100%	000 - 255
10	<b>GREEN FINE</b> 0~100%	000 - 255
11	<b>BLUE</b> 0~100%	000 - 255
12	<b>BLUE FINE</b> 0~100%	000 - 255
13	<b>WHITE</b> 0~100%	000 - 255
14	<b>WHITE FINE</b> 0~100%	000 - 255
15	<b>COLOR MACRO</b> No Function Amber Shift on Color Macro	000 - 002 003 - 005 006 - 255
16	<b>CTO ON COLORS</b> 0~100%	000 - 255
17	<b>DIMMER FADE</b> Read from menu 0~100%	000 - 000 001 - 255

# ECLPANELTWC

## 4 CHANNELS TOUR

MODE 4 Ch	FUNCTION	DMX Value
1	<b>RED</b> 0~100%	000 - 255
2	<b>GREEN</b> 0~100%	000 - 255
3	<b>BLUE</b> 0~100%	000 - 255
4	<b>WHITE</b> 0~100%	000 - 255

## 6 CHANNELS TOUR

MODE 6 Ch	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>RED</b> 0~100%	000 - 255
3	<b>GREEN</b> 0~100%	000 - 255
4	<b>BLUE</b> 0~100%	000 - 255
5	<b>WHITE</b> 0~100%	000 - 255
6	<b>STROBE</b> Closed Strobe slow to fast Open Random slow to fast Open	000 - 030 031 - 100 101 - 130 131 - 200 201 - 255

## 10 CHANNELS TOUR

MODE 10 Ch	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>RED</b> 0~100%	000 - 255
3	<b>GREEN</b> 0~100%	000 - 255
4	<b>BLUE</b> 0~100%	000 - 255
5	<b>WHITE</b> 0~100%	000 - 255

## 10 CHANNELS TOUR

MODE 10 Ch	FUNCTION	DMX Value
6	<b>STROBE</b> Closed Strobe slow to fast Open Random slow to fast Open	000 - 030 031 - 100 101 - 130 131 - 200 201 - 255
7	<b>CCT</b> No Function 2800K 3200K 3500K 4000K 4500K 5000K 5600K 6000K 6500K No Function	000 - 005 006 - 030 031 - 055 056 - 080 081 - 105 106 - 130 131 - 155 156 - 180 181 - 205 206 - 230 231 - 255
8	<b>EFFECTS</b> No Function Effect 1 Effect 2 Effect 3 Effect 4 Effect 5 Candle Cop Car1 Cop Car2 Cop Car3 Fire Fireworks Paparazzi Television Party Clouds Club Color Chase Strobe Lighting Explosion Fluorescent Process Pulsing Welding	000 - 010 011 - 020 021 - 030 031 - 040 041 - 050 051 - 060 061 - 070 071 - 080 081 - 090 091 - 100 101 - 110 111 - 120 121 - 130 131 - 140 141 - 150 151 - 160 161 - 170 171 - 180 181 - 190 191 - 200 201 - 210 211 - 220 221 - 230 231 - 240 241 - 255
9	<b>EFFECTS SPEED</b> Speed slow to fast	000 - 255
10	<b>DIMMER FADE</b> Read from menu 0~100%	000 - 000 001 - 255

# ECLPANELTWC

## 11 CHANNELS TOUR

MODE 11 Ch	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>DIMMER FINE</b> 0~100%	000 - 255
3	<b>RED</b> 0~100%	000 - 255
4	<b>RED FINE</b> 0~100%	000 - 255
5	<b>GREEN</b> 0~100%	000 - 255
6	<b>GREEN FINE</b> 0~100%	000 - 255
7	<b>BLUE</b> 0~100%	000 - 255
8	<b>BLUE FINE</b> 0~100%	000 - 255
9	<b>WHITE</b> 0~100%	000 - 255
10	<b>WHITE FINE</b> 0~100%	000 - 255
11	<b>STROBE</b> Closed Strobe slow to fast Open Random slow to fast Open	000 - 030 031 - 100 101 - 130 131 - 200 201 - 255

## 15 CHANNELS TOUR

MODE 15 Ch	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>DIMMER FINE</b> 0~100%	000 - 255
3	<b>RED</b> 0~100%	000 - 255
4	<b>RED FINE</b> 0~100%	000 - 255
5	<b>GREEN</b> 0~100%	000 - 255
6	<b>GREEN FINE</b> 0~100%	000 - 255

## 15 CHANNELS TOUR

MODE 15 Ch	FUNCTION	DMX Value
7	<b>BLUE</b> 0~100%	000 - 255
8	<b>BLUE FINE</b> 0~100%	000 - 255
9	<b>WHITE</b> 0~100%	000 - 255
10	<b>WHITE FINE</b> 0~100%	000 - 255
11	<b>STROBE</b> Closed Strobe slow to fast Open Random slow to fast Open	000 - 030 031 - 100 101 - 130 131 - 200 201 - 255
12	<b>CCT</b> No Function 2800K 3200K 3500K 4000K 4500K 5000K 5600K 6000K 6500K No Function	000 - 005 006 - 030 031 - 055 056 - 080 081 - 105 106 - 130 131 - 155 156 - 180 181 - 205 206 - 230 231 - 255
13	<b>EFFECTS</b> No Function Effect 1 Effect 2 Effect 3 Effect 4 Effect 5 Candle Cop Car1 Cop Car2 Cop Car3 Fire Fireworks Paparazzi Television Party Clouds Club Color Chase Strobe Lighting Explosion Fluorescent Process Pulsing Welding	000 - 010 011 - 020 021 - 030 031 - 040 041 - 050 051 - 060 061 - 070 071 - 080 081 - 090 091 - 100 101 - 110 111 - 120 121 - 130 131 - 140 141 - 150 151 - 160 161 - 170 171 - 180 181 - 190 191 - 200 201 - 210 211 - 220 221 - 230 231 - 240 241 - 255
14	<b>EFFECTS SPEED</b> Speed slow to fast	000 - 255
15	<b>DIMMER FADE</b> Read from menu 0~100%	000 - 000 001 - 255

# ECLPANELTWC

## 1 PIXEL

MODE 1 pixel	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>STROBE</b> Closed Strobe slow to fast Open Random slow to fast Open	000 - 030 031 - 100 101 - 130 131 - 200 201 - 255
3	<b>DIMMER FADE</b> Read from menu 0~100%	000 - 000 001 - 255
4	<b>RED</b> 0~100%	000 - 255
5	<b>GREEN</b> 0~100%	000 - 255
6	<b>BLUE</b> 0~100%	000 - 255
7	<b>WHITE</b> 0~100%	000 - 255

## 2V PIXELS

MODE 2V pixels	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>STROBE</b> Closed Strobe slow to fast Open Random slow to fast Open	000 - 030 031 - 100 101 - 130 131 - 200 201 - 255
3	<b>DIMMER FADE</b> Read from menu 0~100%	000 - 000 001 - 255
4	<b>RED1</b> 0~100%	000 - 255
5	<b>GREEN1</b> 0~100%	000 - 255
6	<b>BLUE1</b> 0~100%	000 - 255
7	<b>WHITE1</b> 0~100%	000 - 255
8	<b>RED2</b> 0~100%	000 - 255
9	<b>GREEN2</b> 0~100%	000 - 255
10	<b>BLUE2</b> 0~100%	000 - 255
11	<b>WHITE2</b> 0~100%	000 - 255

## 2H PIXELS

MODE 2H pixels	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>STROBE</b> Closed Strobe slow to fast Open Random slow to fast Open	000 - 030 031 - 100 101 - 130 131 - 200 201 - 255
3	<b>DIMMER FADE</b> Read from menu 0~100%	000 - 000 001 - 255
4	<b>RED1</b> 0~100%	000 - 255
5	<b>GREEN1</b> 0~100%	000 - 255
6	<b>BLUE1</b> 0~100%	000 - 255
7	<b>WHITE1</b> 0~100%	000 - 255
8	<b>RED2</b> 0~100%	000 - 255
9	<b>GREEN2</b> 0~100%	000 - 255
10	<b>BLUE2</b> 0~100%	000 - 255
11	<b>WHITE2</b> 0~100%	000 - 255

# ECLPANELTWC

## 4H PIXELS

MODE 4H pixels	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>STROBE</b> Closed Strobe slow to fast Open Random slow to fast Open	000 - 030 031 - 100 101 - 130 131 - 200 201 - 255
3	<b>DIMMER FADE</b> Read from menu 0~100%	000 - 000 001 - 255
4	<b>RED1</b> 0~100%	000 - 255
5	<b>GREEN1</b> 0~100%	000 - 255
6	<b>BLUE1</b> 0~100%	000 - 255
7	<b>WHITE1</b> 0~100%	000 - 255
8	<b>RED2</b> 0~100%	000 - 255
9	<b>GREEN2</b> 0~100%	000 - 255
10	<b>BLUE2</b> 0~100%	000 - 255
11	<b>WHITE2</b> 0~100%	000 - 255
12	<b>RED3</b> 0~100%	000 - 255
13	<b>GREEN3</b> 0~100%	000 - 255
14	<b>BLUE3</b> 0~100%	000 - 255
15	<b>WHITE3</b> 0~100%	000 - 255
16	<b>RED4</b> 0~100%	000 - 255
17	<b>GREEN4</b> 0~100%	000 - 255
18	<b>BLUE4</b> 0~100%	000 - 255
19	<b>WHITE4</b> 0~100%	000 - 255

## 4V PIXELS

MODE 4V pixels	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>STROBE</b> Closed Strobe slow to fast Open Random slow to fast Open	000 - 030 031 - 100 101 - 130 131 - 200 201 - 255
3	<b>DIMMER FADE</b> Read from menu 0~100%	000 - 000 001 - 255
4	<b>RED1</b> 0~100%	000 - 255
5	<b>GREEN1</b> 0~100%	000 - 255
6	<b>BLUE1</b> 0~100%	000 - 255
7	<b>WHITE1</b> 0~100%	000 - 255
8	<b>RED2</b> 0~100%	000 - 255
9	<b>GREEN2</b> 0~100%	000 - 255
10	<b>BLUE2</b> 0~100%	000 - 255
11	<b>WHITE2</b> 0~100%	000 - 255
12	<b>RED3</b> 0~100%	000 - 255
13	<b>GREEN3</b> 0~100%	000 - 255
14	<b>BLUE3</b> 0~100%	000 - 255
15	<b>WHITE3</b> 0~100%	000 - 255
16	<b>RED4</b> 0~100%	000 - 255
17	<b>GREEN4</b> 0~100%	000 - 255
18	<b>BLUE4</b> 0~100%	000 - 255
19	<b>WHITE4</b> 0~100%	000 - 255

# ECLPANELTWC

## 8 PIXELS

MODE 8 pixels	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>STROBE</b> Closed Strobe slow to fast Open Random slow to fast Open	000 - 030 031 - 100 101 - 130 131 - 200 201 - 255
3	<b>DIMMER FADE</b> Read from menu 0~100%	000 - 000 001 - 255
4	<b>RED1</b> 0~100%	000 - 255
5	<b>GREEN1</b> 0~100%	000 - 255
6	<b>BLUE1</b> 0~100%	000 - 255
7	<b>WHITE1</b> 0~100%	000 - 255
8	<b>RED2</b> 0~100%	000 - 255
9	<b>GREEN2</b> 0~100%	000 - 255
10	<b>BLUE2</b> 0~100%	000 - 255
11	<b>WHITE2</b> 0~100%	000 - 255
12	<b>RED3</b> 0~100%	000 - 255
13	<b>GREEN3</b> 0~100%	000 - 255
14	<b>BLUE3</b> 0~100%	000 - 255
15	<b>WHITE3</b> 0~100%	000 - 255
16	<b>RED4</b> 0~100%	000 - 255
17	<b>GREEN4</b> 0~100%	000 - 255
18	<b>BLUE4</b> 0~100%	000 - 255
19	<b>WHITE4</b> 0~100%	000 - 255

## 8 PIXELS

MODE 8 pixels	FUNCTION	DMX Value
20	<b>RED5</b> 0~100%	000 - 255
21	<b>GREEN5</b> 0~100%	000 - 255
22	<b>BLUE5</b> 0~100%	000 - 255
23	<b>WHITE5</b> 0~100%	000 - 255
24	<b>RED6</b> 0~100%	000 - 255
25	<b>GREEN6</b> 0~100%	000 - 255
26	<b>BLUE6</b> 0~100%	000 - 255
27	<b>WHITE6</b> 0~100%	000 - 255
28	<b>RED7</b> 0~100%	000 - 255
29	<b>GREEN7</b> 0~100%	000 - 255
30	<b>BLUE7</b> 0~100%	000 - 255
31	<b>WHITE7</b> 0~100%	000 - 255
32	<b>RED8</b> 0~100%	000 - 255
33	<b>GREEN8</b> 0~100%	000 - 255
34	<b>BLUE8</b> 0~100%	000 - 255
35	<b>WHITE8</b> 0~100%	000 - 255